

Standard Specifications

## RS-555PC-3550

(Brush motors)



- Typical Applications
- Automotive Appliances
  - Precision and Office Equipment > Inkjet Printer
  - Precision and Office Equipment > Laser Printer
  - Home Appliances > Massager, Vibrator

OUTPUT:5.0W-90W (APPROX)

WEIGHT:250g (APPROX)

Carbon Brush

Ferrite magnets

## Specifications

MODEL		VOLTAGE		NO LOAD		AT MAXIMUM EFFICIENCY				STALL			
		OPERATING RANGE	NOMINAL	SPEED	CURRENT	SPEED	CURRENT	TORQUE		OUTPUT	TORQUE		CURRENT
			V	r/min	A	r/min	A	mN·m	g·cm	W	mN·m	g·cm	A
RS-555PC	3550	9 - 30	12	4800	0.17	4240	1.30	25.6	261	11.4	221	2253	9.90